

PA-1000B: 30W Mixer Amplifier

Simple mixer amplifier ideal for use in reception areas, waiting rooms, factories, education, AV and retail applications.


Full range frequency response makes the unit ideal for any voice or background music system.

Features:

- 2 Mic inputs (1/4" jack~3 pin XLR)
- 1 AUX input (1/4" jack)
- Line in ~ line out
- Priority inputs, telephone, mic 1
- Bass and treble control
- 100v/70v Loudspeaker output
- 8Ω/4Ω Low Z output option
- Remote chime option
- Optional 19" rack kit (BKT-PA1000B)
- 2U high



19" Rack Mount Bracket Option: BKT-PA1000B Bracket



Specifications:

Model:	PA-1000B:
Output Power	30W RMS @ 100v/70v 30W RMS 8Ω/4Ω
Inputs	1 x Mic (1/4" jack and 3 pin XLR) 1 x Aux (1/4" jack) 1 x Telephone (screw terminal)
Priority	Telephone, Mic 1
Input Sensitivity/Impedance	Mic 1, 2 = 1/4" jack ~ 1m v / 10kΩ Mic 1, 2 = 3 pin XLR ~ F Aux ~ 100m v / 10kΩ Telephone ~ 0.775v / 600Ω
Frequency Response	60Hz ~ 20KHz
Line In	1v / 10kΩ
Line Out	1v / 600Ω
Power Requirement	230v AC 50Hz
Dimensions	300(W) x 88(H) x 268(D)mm
Weight	4.6kg

