

PA-2000A / PA-4000A / PA-6000A: 60W, 120W, 240W Mixer Amplifiers



Ground-breaking amplifier series which, when released, set new standards in the industry; its modern outlook and host of features pushed it to the forefront of the PA, education, AV and church markets, where it remains today!

Features:

- 6 Inputs (5 x 3 pin XLR, 1 x stereo phono)
 - Telephone input (screw terminals)
 - Priority-telephone, mic 1, mic 2
 - 5 Band graphic equaliser
 - Line in
 - Line out
 - 5 Zone speaker selection
 - Chime & Siren
 - External mute terminal
 - Bar graph LED output VU meter
 - Optional 19" rack kits (BKT-PA2000A, BKT-PA4000A*)
- * Bracket also fits PA6000A



19" Rack Mount Bracket Options:



Specifications:

Model:	PA-2000A:	PA-4000A:	PA-6000A:
Output Power	60W RMS @ 100v/70v 60W RMS @ 8Ω/4Ω	120W RMS @ 100v/70v 120W RMS @ 8Ω/4Ω	240W RMS @ 100v/70v 240W RMS @ 8Ω/4Ω
Inputs	5 x Mic/line (3 pin XLR~F) 1 x Mix/Aux (stereo phono) 1 x Telephone (screw terminal)	5 x Mic/line (3 pin XLR~F) 1 x Mix/Aux (stereo phono) 1 x Telephone (screw terminal)	5 x Mic/line (3 pin XLR~F) 1 x Mix/Aux (stereo phono) 1 x Telephone (screw terminal)
Priority	Telephone, Mic 1, Mic 2	Telephone, Mic 1, Mic 2	Telephone, Mic 1, Mic 2
Input Sensitivity/Impedance	Inputs 1~6~1mV / 10kV Telephone -2dB/600W	Inputs 1~6~1mV / 10kV Telephone -2dB/600W	Inputs 1~6~1mV / 10kV Telephone -2dB/600W
Frequency Response	60Hz~20KHz	60Hz~20KHz	60Hz~20KHz
Link in/out	In: 0dB/47kΩ Out: -6dB/600Ω	In: 0dB/47kΩ Out: -6dB/600Ω	In: 0dB/47kΩ Out: -6dB/600Ω
Power Requirement	230v AC 50Hz	230v AC 50Hz	230v AC 50Hz
Dimensions	420(W) x 100(H) x 320(D)mm	420(W) x 133(H) x 320(D)mm	420(W) x 133(H) x 320(D)mm
Weight	10kg	12kg	13.5kg

