

PA-935A: 35W Mixer Amplifier

Simple, compact mixer amplifier ideal for use in smaller installations such as waiting rooms, offices, factories, educational and retail applications.


Provides clear voice and full range BGM reproduction.

Features:

- Compact design
- 1 Mic input (1/4" jack)
- 2 Mic/AUX switchable (1/4" jack/stereo phono)
- Priority inputs, telephone, mic 1
- Bass/treble control
- 100v/8Ω/4Ω Low Z output option
- Optional 19" rack kit (BKT-PA935A)



19" Rack Mount Bracket Option: BKT-PA935A Bracket



Specifications:

Model:	PA-935A:
Output Power	35W RMS @ 100v/70v 35W RMS 8Ω/4Ω
Inputs	1 x Mic (1/4" jack) 1 x Mic/Aux (1/4" jack) 1 x Mic/Aux~Sat (1/4" jack and stereo phono) 1 x Screw terminal (Tel)
Priority	Telephone, Mic 1
Input Sensitivity/Impedance	Mic 1,2,3 ~ -50dB/600Ω Aux ~ -15dB/10kΩ Sat ~ 0dB/10kΩ Telephone ~ 0.775v/600Ω
Frequency Response	80Hz~15KHz
Power Requirement	230v AC 50Hz
Dimensions	290(W) x 76(H) x 185(D)mm
Weight	4.4kg

