

o A-60 / A-120: 60W, 120W Mixer Amplifiers

This simple economical desktop amplifier series provides a cost effective solution to basic PA and background music applications.


A-60/A-120 Amplifiers are extensively used throughout the UK's leading high street and supermarket retail outlets.

Features:

- Clean, functional design
- 3 Mic inputs (combi XLR / ¼" jack)
- 2 AUX inputs (stereo phono)
- Bass and treble control
- Priority input - mic 1
- Phoenix screw terminal for loudspeaker connection
- 2U high
- Optional 19" rack (BKT-A120*)

* Also fits A-60 Amplifiers

o 19" Rack Mount Bracket Option: BKT-A120 Bracket



Specifications:

Model:	A-60:	A-120:
Output Power	60W RMS @ 100v/70v 60W RMS @ 4Ω	120W RMS @ 100v/70v 120W RMS @ 4Ω
Inputs	3 x Mic (combi ¼" XLR) 2 x Aux (stereo phono)	3 x Mic (combi ¼" XLR) 2 x Aux (stereo phono)
Priority	Mic 1	Mic 1
Input Sensitivity/Impedance	Mic 1,2,3 ~ -60dB/600Ω Aux ~ -10dB/10kΩ unbalanced	Mic 1,2,3 ~ -60dB/600Ω Aux ~ -10dB/10kΩ unbalanced
Frequency Response	80Hz~16KHz	80Hz~16KHz
Power Requirement	230v AC 50Hz	230v AC 50Hz
Dimensions	420(W) x 88(H) x 320(D)mm	420(W) x 88(H) x 320(D)mm
Weight	8.9kg	10.3kg

